

▶▶▶ Power Distribution Unit



FT-PDU8250

Designated Power Distribution Unit for Cabinet

- Socket Type: IEC60906 Socket(NEMA5-15R)[9]
- Power Input: Left end single input
- Bracket Install: Frontal installation
- Protection Function: No protection function
- Cable : 3 x 1.5 mm² x 2M
- Rating voltage: 250VAC 50/60Hz
- Fittings: 2pcs $\phi 6 \times 16$ mm cross bolt, 2pcs M6 float nut, PDU manual
- Socket Quantity: 9 way
- Max. power: 2500W
- Cable with plug: IEC60906 plug(NEMA 5-15P 15A)
- Control Function: Single power indicator
- PDU Size: 481.5 x 68 x 44.4 mm(L*W*H*)
- RoHS



FT-PDU8U250

Designated Power Distribution Unit for Cabinet

- Socket Type: GB2099.3 Socket [8]
- Power Input: Left end single input
- Bracket Install: Frontal installation
- Protection Function: No protection function
- Cable : 3 x 1.5 mm² x 2M
- Rating voltage: 250VAC 50/60Hz
- Fittings: 2pcs $\phi 6 \times 16$ mm cross bolt, 2pcs M6 float nut, PDU manual
- Socket Quantity: 8 way, Universal PDU series
- Max. power: 3750W
- Cable with plug: IEC60906 plug(NEMA 5-15P 15A)
- Control Function: no control function
- PDU Size: 481.5 x 68 x 44.4 mm(L*W*H*)
- RoHS



FT-PDU9U110L

Designated Power Distribution Unit for Cabinet

- Socket Type: IEC60906 Socket(NEMA5-15R)[9]
- Power Input: Left end single input
- Bracket Install: Frontal installation
- Protection Function: No protection function
- Cable : 3 x 1.5 mm² x 2M
- Rating voltage: 110VAC 50/60Hz
- Fittings: 2pcs $\phi 6 \times 16$ mm cross bolt, 2pcs M6 float nut, PDU manual
- Socket Quantity: 9 way
- Max. power: 1650W
- Cable with plug: IEC60906 plug(NEMA 5-15P 15A)
- Control Function: Single power indicator
- PDU Size: 481.5 x 68 x 44.4 mm(L*W*H*)
- RoHS